

MLFB-Ordering data

6SL3210-1KE12-3UP2



Figure similar

Client order no.: Order no. : Offer no. : Remarks:

Item no.: Consignment no. : Project:

Rated data				
nput				
Number of phases	3 AC			
Line voltage	380 480 V +10 % -20 %			
Line frequency	47 63 Hz			
Rated current (LO)	2.90 A			
Rated current (HO)	2.50 A			
Output				
Number of phases	3 AC			
Rated voltage	400 V			
Rated power IEC 400V (LO)	0.75 kW			
Rated power NEC 480V (LO)	1.00 hp			
Rated power IEC 400V (HO)	0.55 kW			
Rated power NEC 480V (HO)	0.75 hp			
Rated current (IN)	2.30 A			
Rated current (LO)	2.20 A			
Rated current (HO)	1.70 A			
Max. output current	3.40 A			
Pulse frequency	4 kHz			
Output frequency for vector control	0 240 Hz			
Output frequency for V/f control	0 550 Hz			

Overload capabi	lity
-----------------	------

Low Overload (LO)

150 % base load current IL for 3 s, followed by 110 % base load current IL for 57 s in a 300 s cycle time

High Overload (HO)

200 % base load current IH for 3 s, followed by 150 % base load current IH for 57 s in a 300 s cycle time

General tech. specifications			
Power factor λ	0.70 0.85		
Offset factor cos φ	0.95		
Efficiency η	0.97		
Sound pressure level (1m)	49 dB		
Power loss	0.04 kW		
Filter class (integrated)	Unfiltered		

Ambient conditions		
Cooling	Air cooling using an integrated fan	
Cooling air requirement	0.005 m³/s (0.177 ft³/s)	
Installation altitude	1000 m (3280.84 ft)	
Ambient temperature		
Operation	-10 40 °C (14 104 °F)	
Transport	-40 70 °C (-40 158 °F)	
Storage	-40 70 °C (-40 158 °F)	
Relative humidity		

95 % At 40 °C (104 °F), condensation Max. operation and icing not permissible

Closed-loop control techniques			
V/f linear / square-law / parameterizable	Yes		
V/f with flux current control (FCC)	Yes		
V/f ECO linear / square-law	Yes		
Sensorless vector control	Yes		
Vector control, with sensor	No		
Encoderless torque control	No		
Torque control, with encoder	No		



MLFB-Ordering data

6SL3210-1KE12-3UP2



03	13210 IKE12 3012		Figure simil		
Mechanical data		Com	Communication		
Degree of protection	IP20 / UL open type	Communication	PROFIBUS DP		
Size	FSAA	Connections			
Net weight	1.40 kg (3.09 lb)	Signal cable			
Width	73 mm (2.87 in)	Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)		
Height	173 mm (6.81 in)	Line side			
Depth	155 mm (6.10 in)	Version	Plug-in screw terminals		
Inputs / out	tputs	Conductor cross-section	1.00 2.50 mm² (AWG 18 AWG 14)		
Standard digital inputs		Motor end			
Number	6	Version	Plug-in screw terminals		
Switching level: 0→1	11 V	Conductor cross-section	1.00 2.50 mm² (AWG 18 AWG 14)		
Switching level: 1→0	5 V	DC link (for braking resistor))		
Max. inrush current	15 mA	Version	Plug-in screw terminals		
Fail-safe digital inputs		Conductor cross-section	1.00 2.50 mm ² (AWG 18 AWG 14)		
Number	1	Line length, max.	15 m (49.21 ft)		
Digital outputs		PE connection			
Number as relay changeover contact	1	Max. motor cable length	On housing with M4 screw		
Output (resistive load)	DC 30 V, 0.5 A	Shielded	50 m (164.04 ft)		
Number as transistor	1	Unshielded	100 m (328.08 ft)		
Output (resistive load)	DC 30 V, 0.5 A	S	tandards		
Analog / digital inputs		Compliance with standards	UL, cUL, CE, C-Tick (RCM)		
Number	1 (Differential input)				
Resolution	10 bit	CE marking	EMC Directive 2004/108/EC, Low-Voltage Directive 2006/95/EC		
Switching threshold as digital in	put				
0→1	4 V				
1→0	1.6 V				
Analog outputs					
Number	1 (Non-isolated output)				

PTC/ KTY interface

1 motor temperature sensor input, sensors that can be connected: PTC, KTY and Thermo-Click, accuracy $\pm 5~^\circ\text{C}$



MLFB-Ordering data


6SL3210-1KE12-3UP2



Figure similar

Converter losses to EN 50598-2*

Efficiency class	IE2
Comparison with the reference converter (90% / 100%)	-80.87 %



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard EN 50598) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

*converted values