

MLFB-Ordering data

6SL3210-1KE13-2UP2



Figure similar

Client order no. : Order no. : Offer no. : Remarks :

ltem no. :
Consignment no. :
Project :

Rated da	ata	General tech. specifications		
Input		Power factor λ	0.70 0.85	
Number of phases	3 AC	Offset factor cos φ	0.95	
Line voltage	380 480 V +10 % -20 %	Efficiency η	0.97	
Line frequency	47 63 Hz	Sound pressure level (1m)	49 dB	
Rated current (LO)	4.10 A	Power loss	0.05 kW	
Rated current (HO)	3.20 A	Filter class (integrated)	Unfiltered	
Output		A		
Number of phases	3 AC	Ambient conditions		
Rated voltage	400 V	Cooling	Air cooling using an integrated fan	
Rated power IEC 400V (LO)	1.10 kW			
Rated power NEC 480V (LO)	1.50 hp	Cooling air requirement	0.005 m ³ /s (0.177 ft ³ /s)	
Rated power IEC 400V (HO)	0.75 kW	Installation altitude	1000 m (3280.84 ft)	
Rated power NEC 480V (HO)	1.00 hp	Ambient temperature		
Rated current (IN)	3.20 A	Operation	-10 40 °C (14 104 °F)	
Rated current (LO)	3.10 A	Transport	-40 70 °C (-40 158 °F)	
Rated current (HO)	2.20 A	Storage	-40 70 °C (-40 158 °F)	
Max. output current	4.40 A	Relative humidity		
Pulse frequency	4.000 kHz	Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible	
Output frequency for vector control	0 240 Hz	Closed-loop control techniques		
Output frequency for V/f control	0 550 Hz	V/f linear / square-law / parameterizable Yes		
		V/f with flux current control (FC		
Overload capability		V/f ECO linear / square-law	Yes	
Low Overload (LO) 150 % base load current IL for 3 s, followed by 110 % base load current IL for 57 s in a 300 s cycle time		Sensorless vector control	Yes	
		Vector control, with sensor	No	
		Encoderless torque control	No	

High Overload (HO)

200 % base load current IH for 3 s, followed by 150 % base load current IH for 57 s in a 300 s cycle time

Torque control, with encoder

No



MLFB-Ordering data

6SL3210-1KE13-2UP2



Figure similar **Mechanical data** Communication Degree of protection IP20 / UL open type PROFIBUS DP Communication Size FSAA **Connections** Net weight 1.40 kg (3.09 lb) Signal cable Width 73 mm (2.87 in) Conductor cross-section 0.15 ... 1.50 mm² (AWG 24 ... AWG 16) Height 173 mm (6.81 in) Line side Depth 155 mm (6.10 in) Version Plug-in screw terminals Inputs / outputs Conductor cross-section 1.00 ... 2.50 mm² (AWG 18 ... AWG 14) **Standard digital inputs** Motor end Number 6 Version Plug-in screw terminals Switching level: 0→1 11 V **Conductor cross-section** 1.00 ... 2.50 mm² (AWG 18 ... AWG 14) Switching level: 1→0 5 V DC link (for braking resistor) Max. inrush current 15 mA Plug-in screw terminals Version Fail-safe digital inputs Conductor cross-section 1.00 ... 2.50 mm² (AWG 18 ... AWG 14) Number 1 Line length, max. 15 m (49.21 ft) **Digital outputs PE** connection On housing with M4 screw Number as relay changeover contact 1 Max. motor cable length **Output (resistive load)** DC 30 V, 0.5 A Shielded 50 m (164.04 ft) Unshielded Number as transistor 100 m (328.08 ft) Output (resistive load) DC 30 V, 0.5 A **Standards** Analog / digital inputs Compliance with standards UL, cUL, CE, C-Tick (RCM) Number 1 (Differential input) EMC Directive 2004/108/EC, Low-Voltage **CE** marking Resolution 10 bit Directive 2006/95/EC Switching threshold as digital input 0→1 4 V 1→0 1.6 V

Analog outputs

Number

1 (Non-isolated output)

PTC/ KTY interface

1 motor temperature sensor input, sensors that can be connected: PTC, KTY and Thermo-Click, accuracy $\pm 5\ ^\circ C$



MLFB-Ordering data

6SL3210-1KE13-2UP2



Figure similar

Converter losses to EN 50598-2*

Efficiency class IE2 Comparison with the reference converter (90% / -77.61 % 100%) -**O**-^{49.1 W (2.29 %)} 40.6 W (1.89 %) 44.0 W (2.06 %) 100% 33.6 W (1.56 %) 35.2 W (1.64 %) 37.2 W (1.74 %) 50% 30.8 W (1.43 %) 32 W (1.46 %) 25% f 50% 90%

The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard EN 50598) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

*converted values