



Catalog No. CR306E002

Description: (STOCK) #3 STARTER

UPC No

Home > Starters > NEMA > Full Voltage Starters

- NEMA Rated Full Voltage Magnetic Starters.
- Three-Phase Magnetic Starters.
- Nonreversing.
- Non-combination.
- Open.
- NEMA Size 3 with Thermal Overload Relay.
- 600 Volts Maximum 50/60 Hertz. Continuous Amperage rating 90.



Representative Image

Descriptors

Category

Full Voltage Starters