SIEMENS

Data sheet

6GK5004-1BF00-1AB2



SCALANCE XB004-1LD unmanaged Industrial Ethernet Switch for 10/100 Mbit/s; for setting up small star and line topologies; LED diagnostics, IP20, 24 V AC/DC power supply, with 4x 10/100 Mbit/s twisted pair ports with RJ45 sockets; 1 x 100 Mbit/s single-mode glass FOC port with SC socket; Manual available as a download

Product type designation	SCALANCE XB004-1LD	
Transfer rate		
Transfer rate	10 Mbit/s, 100 Mbit/s	
Interfaces / for communication / Integrated		
Number of electrical connections		
 for network components or terminal equipment 	4; RJ45	
Number of 100 Mbit/s SC ports		
• for multimode	0	
• for single mode (LD)	1	
Interfaces / other		
Number of electrical connections		
• for power supply	1	
Type of electrical connection		
• for power supply	3-pole terminal block	
Supply voltage, current consumption, power loss		
Type of voltage / of the supply voltage	AC/DC	
Supply voltage		

• external	24 V
• external / minimum	19.2 V
• external / maximum	28.8 V
• at AC	24 V
Product component / fusing at power supply input	Yes
Fuse protection type / at input for supply voltage	0.6 A / 60 V
Consumed current / maximum	0.1 A
Power loss [W]	
• at DC / at 24 V	2.4 W

Ambient conditions	
Ambient temperature	
 during operation 	-10 +60 °C
during storage	-40 +80 °C
during transport	-40 +80 °C
Relative humidity	
 at 25 °C / without condensation / during 	95 %
operation / maximum	
Protection class IP	IP20
Design	Box
Width	45 mm
Height	100 mm
Depth	87 mm
Net weight	0.165 kg
Mounting type	
• 35 mm DIN rail mounting	Yes
wall mounting	Yes
• S7-1500 rail mounting	No

Product functions / management, configuration, engineering	
Product function	
 multiport mirroring 	No
• CoS	Yes
PROFINET conformity class	Α
Product function / switch-managed	No

Product functions / redundancy Product function • Parallel Redundancy Protocol (PRP)/operation in the PRP-network • Parallel Redundancy Protocol (PRP)/Redundant Network Access (RNA)

Standards, specifications, approvals	
Standard	

• for FM FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2,

GP. IIC, T4

• for hazardous zone EN 60079-0:2009, EN60079-15:2010, II 3 G Ex nA IIC T4 Gc,

KEMA 07ATEX0145 X

• for safety / from CSA and UL UL 60950-1, CSA C22.2 No. 60950-1

• for emitted interference EN 61000-6-4 (Class A)

• for interference immunity EN 61000-6-2

Standards, specifications, approvals / CE

Certificate of suitability / CE marking Yes

Standards, specifications, approvals / other

Certificate of suitability EN 61000-6-2, EN 61000-6-4

C-TickKC approvalYes

Standards, specifications, approvals / Product conformity

MTBF 238 y

Further information / Internet-Links

Internet-Link

• to website: Selector SIMATIC NET SELECTION TOOL

• to website: Industrial communication

• to website: Industry Mall

• to website: Information and Download Center

• to website: Image database

• to website: CAx Download Manager

• to website: Industry Online Support

http://www.siemens.com/snst

http://www.siemens.com/simatic-net

https://mall.industry.siemens.com

http://www.siemens.com/industry/infocenter

http://automation.siemens.com/bilddb

http://www.siemens.com/cax

https://support.industry.siemens.com

Security information

Security information

Siemens provides products and solutions with industrial security functions that support the secure operation of plants, solutions, machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly check for product updates. For the secure operation of Siemens products and solutions, it is necessary to take suitable preventive action(e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Thirdparty products that may be in use should also be considered. For more information about industrial security, visit http://www.siemens.com/industrialsecurity. To stay informed about product updates as they occur, sign up for a product-specific newsletter. For more information, visit http://support.automation.siemens.com. (V3.4)

11/11/2019 last modified: